

ŰL)_{us}

PGR-3200 SERIES

Insulation Monitor



Simplified Circuit Diagram



Ordering Information

| ORDERING NUMBER | CONTROL POWER |
|-----------------|------------------------|
| PGR-3200 | 240 Vac ⁽¹⁾ |
| PGR-3200-120 | 120 Vac |
| | |
| ACCESSORIES | REQUIREMENT |
| PGH Series | Required >1,300 V |
| PGA-0510 | Optional |

Note: For optional conformal coating please consult factory. To convert to a resistance grounded system, see neutral-grounding-resistors packages.

(1) UL Not Available

Description

The PGR-3200 detects ground faults by continuously monitoring the insulation integrity of ungrounded electrical systems. The relay monitors the insulation for damage and assists with predictive maintenance and troubleshooting of developing ground faults by providing two warning and an alarm level. The PGR-3200 operates on one- or three-phase ungrounded systems up to 6 kV.

The PGR-3200 can also be used on a grounded system to monitor the insulation for damage, while the power system is de-energized. The mode-of-operation terminals (27-28) are connected to the circuit breaker or contactor auxiliary contacts to toggle the relay off when the contactor or breaker is closed.

Features & Benefits

| FEATURES | BENEFITS |
|-----------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| NEC [®] and CEC Code compliant | Meets National Electrical Code (NEC®) Article 250.21(B) and Canadian Electrical Code Part 1, Section 10-106 (2) requirements for ungrounded systems |
| Output contact (50 kΩ) | Form C output contact for alarming when the insulation resistance is below 50 $\ensuremath{\kappa}\Omega$ |
| Output contact (10 kΩ) | Form C output contact for tripping when the insulation resistance is below 10 $\ensuremath{k\Omega}$ |
| Analog output (0-1 mA) | Provides means for connecting to an optional meter (PGA-0510) or control system |
| DIN-rail or surface mount | Flexible options for ease of installation |

Accessories



PGH Series High-Tension Coupler A PGH Series high-tension coupler is

required for systems between 1,300 V and 6,000 V.



PGA-0510 Analog Ohm Meter

Optional PGA-0510 Analog Meter allows for metering of insulation resistance.

Specifications

IEEE Device Numbers

Input Voltage Dimensions Resistance Ratings

Contact Operating Mode Test Button Reset Button Output Contacts Analog Output Conformally Coated Approvals Warranty Mounting Undervoltage Relay (27) Ground Detector Relay (64) See ordering information **H** 75 mm (3"); **W** 100 mm (3.9"); **D** 115 mm (4.5") Insulation warning (30 k Ω and 50 k Ω) Insulation alarm (10 k Ω) Non-fail-safe Local Local and remote Two Form C 0-1 mA Consult factory UL Listed (E183688) 5 years DIN, Surface